

## AVerMedia 4 EYES Pro

### Digital Video Recording for your Surveillance System (Windows-based)

AVerMedia 4 EYES Pro, stackable video capture card (up to 4 cards), works as the real time digital video recording solution and allows you to capture true color images and videos from 4 up to 16 cameras simultaneously (cameras not included). With the latest Motion Detection technology, once any movement is detected in the monitoring area, AVerMedia EYES Pro Series automatically starts recording and triggers the alarm.

#### FEATURES:

- Display Rate (Total): See chart below
- Recording Rate (Total): See chart below
- O/S Support: Microsoft Windows® 98SE, Windows® Me, Windows® 2000, and Windows® XP
- Upgradeable from 4 cameras to 16 cameras
- Support Pan/Tilt/Zoom cameras
- Alert on event (Sensor/Relay/Motion Detection). Configurable for each camera
- Multi-tasking: Simultaneous monitoring, recording, playback, and remote monitoring
- Display Mode: Auto scan with full screen display under 1/4/9/12/16 cameras display mode
- Video Search: Sort recorded files by year, month, date, hour, minute, and second. Files can be played consecutively
- Event Search: Search recorded files by events (motion, audio, call out, sensor input, relay output, video loss, and alarm recording)
- Intelligent Search: Using mask to search motions from massive recorded files
- Multiple playback: 1/4/9/16 channels playback in the same time
- Backup Mode: Manual backup and schedule backup
- Backup Device: Disk Array, Tape Drive, CD-R and ZIP Drive
- Alarm Messages: Fax or send alarm message to pagers, mobile, landline phones, mailbox and e-mail.
- Remote Transmission: LAN and Internet (via Modem/ADSL/ISDN)
- Remote Manager: Remote monitoring, recording, playback, backup, Pan/Tilt/Zoom control, and Center Station function. (Up to 16 servers)
- Video Recording Mode: Alarm trigger/Motion Detection/Continuous/Schedule recording/Recycle recording
- Masking blank zones under recording mode

- Motion Detection: Programmable multiple detection zones for each camera
- Access control protected by passwords
- Remote backup ensures data security

#### SPECIFICATIONS:

- VGA Output Resolution: 1024 x 768
- Video Compression: Motion JPEG
- Image Resolution: 320 x 240 or 640 x 480
- Sensor Input: Up to 16
- Relay Output: Up to 12
- Recorded Video Format: DSS
- Recorded Audio Format: WAV
- Warranty: One year limited parts & labor
- Compliance: FCC Class A


#### SYSTEM REQUIREMENTS:

- CPU: Pentium® III 800 mhz or above
- RAM: 128MB (recommend 256MB)
- Motherboard: Intel® 815/845 chipset
- HDD: 80GB or above
- VGA: 32MB RAM (recommend 64MB)
- Operating System: Windows®98SE/ME/2000/XP (recommend Windows 2000)
- Video Input: 4/8/12/16 NTSC/PAL cameras (BNC connector), Support PTZ Cameras (Cameras not included)

#### PACKAGE INCLUDES:

- Video capture card (each card has 4 video inputs)
- User Manual
- EYES Pro Software CD (Including Driver, Application Software, and User's Manual)

#### PRODUCT PERFORMANCE:

				
Product	4 EYES Pro	(2x) 4 EYES Pro	(3x) 4 EYES Pro	(4x) 4 EYES Pro
Manuf. SKU	NVEYESPR4	NVEYESPR4	NVEYESPR4	NVEYESPR4
Video Card	1 Video Card	2 Video Cards	3 Video Cards	4 Video Cards
Video Input	4 channels	8 channels	12 channels	16 channels
Total Display Rate (NTSC/PAL)	30/25 fps	60/50 fps	90/75 fps	120/100 fps
Total Recording Rate (NTSC/PAL)	25/25 fps	50/50fps	75/75 fps	100/100 fps